

#### Description

The Alemlube 20055 LED Flood Light is the ultimate work light providing superior illumination for many applications in the workshop, in factories, around the home and for outdoor use. Any one of three brightness levels can be selected giving up to 8 hours of use before recharging is required.

The 20055 also features an intelligent charge indicator, a 180° adjustable stand for multi-purpose use and a robust aluminium structure ensures reliable performance and longevity.

Furthermore, the 20055 LED Flood Light embodies superior impact and water resistance ratings.

#### Technical Details

Item No.	20055
Light Source	High Power LED - Flood Light
Luminous Power	ca. 2100 lm - Full Power Mode ca. 1000 lm - Normal Mode ca. 500 lm - ECO Light
Operating Time	ca. 2.5 h - Full Power Mode ca. 5 h - Normal Mode ca. 9 h - ECO Mode
Battery Specification	Li-Ion 11.1 V, 4400 mAh, 48.84 Wh
Charging Time	ca. 3.5 h
Charging Input	DC 15V 1.5A
Degree of Protection	IP 65, IK 07
Operating Temperature	-10 °C to +40 °C



### Safety Warning and Precautions

1. Do not open the device.
2. Do not look directly into the light emitting lamp - Risk of eye injuries!
3. Do not operate in direct sun light or extreme temperature conditions
4. Operating temperature, -10°C to +40°C.
5. Keep away from children! Children should be supervised in order to ensure that they do not play with the device!

### Operating & Charging Procedure

1. 20055 operating mode as below
  - Press the switch first time, the main light switches to ECO mode.
  - Press the switch second time, the main light switches to normal mode.
  - Press the switch third time, the main light switches to full power mode.
  - Press the switch fourth time, whole light switches off.
2. Switch lamp off during charging, and connect the charger to the light.
3. The battery indicator will blink during charging.
4. The battery indicator will stay lit after the charging is finished.
5. If the battery indicator did not light up, please remove the charger and try again.
6. Always only use the recommended charger to charge the lamp.  
The use of a NON-recommended charger can lead to a fire and destroy the lamp.
7. Before taking the flood light into service for the first time charge it for 4-5 hours.
8. Fully charge the flood light before it is stored for a longer period.

### Safety Instructions

1. Do not use the device if there is damage to the housing, plug or cable.
2. Do not open the device! Repair work and replacing the rechargeable battery pack may only be carried out by an authorised electrician.
3. Carry out cleaning tasks only when the mains plug is removed from the mains power!
4. There is a risk of short-circuit. Repairs on the device may only be carried out by commissioned and trained persons.  
Please contact your nearest authorized branch.
5. Protect the battery against heat, e.g., against continuous intense sunlight, fire, water, and moisture.
6. If the battery is damaged or not used correctly fluids can leak from the battery. Avoid contact with these.  
Leaking battery fluids can lead to skin irritation or burns. Rinse off with water if you should come into contact.  
If the fluid gets into your eyes, ensure you get medical help.

### Environmental Protection

1. The device should not be discarded in the normal household waste under any circumstances.
2. Dispose of the device via an authorised disposal centre or your communal waste disposal facility.  
Observe the current applicable - regulations. Contact your waste disposal facility in the event of any doubt.  
Dispose of all packaging materials via an environmentally friendly disposal facility. Rechargeable batteries must not be disposed of in the household waste.
3. Return used rechargeable batteries to your dealer or hand them in to a battery collection facility.